

A VENUE CUSTOMIZABLE WHITE BALANCE
DIGITAL CAMERA SYSTEM

CROSS REFERENCE TO RELATED APPLICATIONS

5 This application is related to U.S. Application Serial Number
09/224,547 entitled "Producing Panoramic Digital Images By Digital Camera
Systems", filed December 31, 1998 by May et. al., having Kodak docket number
77,751 and the disclosure of which is herein incorporated by reference.

BACKGROUND OF THE INVENTION

FIELD OF THE INVENTION

10 The present invention is directed to a system that allows a digital
camera user to store white balance settings for different venues and, more
particularly, to a system that will allow the user to return to the venue and retrieve
15 the corresponding setting for use at the venue and use the retrieved setting to
process the digital images.

DESCRIPTION OF THE RELATED ART

20 Digital cameras, such as the Kodak DC210+ camera, allow the user
to select a variety of white balance settings. These include manual settings for
different "average" illuminants, such as daylight or tungsten, as well as an
automatic setting that determines the proper white balance setting for each
captured picture using the pixel values of the image and possibly other camera
information, such as the overall scene luminance level and the flash mode. In the
25 DC210+, it is also possible to "lock" the automatically determined white balance
setting after taking a first picture, so that subsequent pictures are taken with the
same white balance correction value, as described in "Producing Panoramic
Digital Images By Digital Camera Systems" noted above. This can be useful
when taking a series of still images to be stitched together or viewed one after
30 another. However, in these systems only one "locked" value is stored, and once
the lock mode is disabled, or a new lock value is stored, the previous white

balance value is erased and cannot be recalled by the camera.

News photographers, sports photographers, etc. often return to the same venue many times per month to take pictures of the same type of event (e.g. a hockey game or a baseball game). Each venue has different types of lighting which requires different white balance correction values to make white or neutral objects in the scene appear white in the captured image.

What is needed is a digital camera featuring a simple way for the user to accurately determine the appropriate white balance setting only one time at each venue, and then recall the setting the next time the user takes pictures at the same venue.

SUMMARY OF THE INVENTION

It is an object of the present invention to provide a system that allows a user to set and save white balance settings for different venues.

It is another object of the present invention to provide a system that allows a user to retrieve and use white balance settings for different venues.

The above objects can be attained by a digital camera system that allows a user to capture an image including a white balance reference for a particular picture taking venue, determine a white balance setting from the image and save the white balance setting for future picture taking sessions at that venue. The setting is saved in a non-volatile memory that can be removed from and inserted into the digital camera. The white balance setting is saved in a file folder having an identifier or file name allowing the user to correlate the file name with the particular venue. The white balance setting can be determined by the digital camera or in an associated computer and the captured images can be corrected in the digital camera or in the associated computer.

These together with other objects and advantages which will be subsequently apparent, reside in the details of construction and operation as more fully hereinafter described and claimed, reference being had to the accompanying drawings forming a part hereof, wherein like numerals refer to like parts throughout.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram of the components of the present invention.

5 FIG. 2 shows the boards of a preferred embodiment.

FIG. 3 depicts a flow of operations when setting, saving and using a white balance.

FIG. 4 shows a flow of operations of a white balance interface.

FIGS. 5A - 5K illustrate GUI screens.

10

DESCRIPTION OF THE PREFERRED EMBODIMENTS

A digital camera system, according to the present invention, typically includes a manual white balance setting feature that allows the white balance for a particular picture taking session or venue to be determined using a white card or other object positioned in the center of a captured image. White balance settings each for a different venue can be stored within a non-volatile memory in the digital camera of the invention. These settings can be used to process images captured at the venue in the digital camera before the images are stored or output. When future pictures are to be taken at the same venue, in accordance with the invention, the appropriate white balance settings can be retrieved and used, without having to repeat the manual white balance process. Other venue-image settings, such as image sharpness, image contrast, or image colorfulness, can also or alternatively be stored in the digital camera and later recalled and used. It is also useful to include other venue specific settings in a venue file, such as default exposure mode, shutter or aperture settings, focus mode, and other photographic settings. These typically vary with the type of sport or event. Retrieving and loading such settings would configure the digital camera to the best starting configuration but allow the photographer to vary individual settings as needed for the venue/event.

30 An alternative method of creating a white balance setting is by viewing any image captured at a venue on a computer screen and clicking on a

neutral or white object in the scene. This is called "click balance" and it does not require the special image capture of a gray card but does require a picture with some neutral object in the scene.

It is also possible, for digital cameras with less processing power to
5 store the white balance settings for the venue on a removable memory, such as a memory card, for later use in computer processing of taken images or to store a reference image having the white balance reference card therein for later white balance determination by the computer. That is, the determination of a white balance setting can be performed by the computer and stored in a file with an
10 appropriate venue name on the removable memory card. The white balance correction for a set of pictures can also be performed by the computer using a setting selected at the venue and stored in association with a set of pictures on the card.

A digital camera system 10 according to the present invention
15 includes a digital camera 12 typically having components as shown in the block diagram of FIG. 1. The digital camera 12 includes a lens 14, an image sensor 16, such as a CCD image sensor, a separate photo diode exposure detector 18, and an optical viewfinder 19 (associated display memory 20 and display 21) for composing the scene. In alternative embodiments, the image sensor 16 could also
20 be used as the exposure detector. Once the picture is composed, the user presses a shutter button 22, which has two positions, S1 (partially depressed) and S2 (fully depressed). When S1 is enabled, the digital camera 12 performs automatic exposure determination via system 23 using the photo detector signal, which sets the f-number, exposure time, and analog gain level. The digital camera exposure
25 control may operate as described in Kodak U.S. Patent No. 5,610,654 entitled "Automatic Camera Exposure Control Using Variable ISO Sensor" the disclosure of which is herein incorporated by reference.

A digital camera control processor and timing generator or control
24 then generates the control signals that expose the image sensor 16 via shutter
30 drive 25 and shutter 26, and clock out the sensor signal. The analog signal from the sensor 16 is processed in an analog signal processor 27 (which performs

correlated double sampling), A/D converted by converter 28, and stored in frame memory 29. An image processor 30 includes and performs color filter array interpolation, white balance correction, color correction, edge enhancement, JPEG image compression, and file formatting. The resulting image is stored in an image file, such as a JPEG interchange format file (.JPG), on a removable memory card 5 32 through an interface 31.

When the user sets the white balance to the "automatic" mode, the white balance settings to be used for each image can be individually determined automatically by a white balance determination processor 34, stored in white balance memory 36 and used to correct the white balance as described in Kodak 10 U.S. Patent No. 5,659,357, entitled "Auto White Adjusting Device", by Miyano the disclosure of which is herein incorporated by reference. However, this can lead to white balance errors since the algorithm can be fooled by colored objects in the scene.

For best results, the proper white balance setting for a particular 15 venue is determined by photographing a large white or gray white balance reference card positioned in the scene to be photographed. For a sports venue, this means holding the card on the ice of a hockey rink or in the middle of a baseball field. Typically, the photographer does not want to do this each time they 20 take pictures at a given venue. To avoid this problem, the present invention allows the white balance obtained for the venue to be saved.

The present invention allows the user to perform the white card photography only once per venue. The white balance setting for each venue is determined and stored in a file named by the user. The file can be created/located 25 in the camera white balance memory 36 and/or in the removable memory card 32 and duplicated on a separate computer 38, such as a desktop computer, available to the user. When the user returns to the venue, the user can select the named white balance file, and that file will be used to perform the white balance correction for future images until the setting is canceled or changed. The user can 30 also transfer the setting to additional digital cameras through the computer 38 or removable memory card 32, so that the same setting determined by one digital

camera can be used by other digital cameras that are photographing the same event.

5 A preferred configuration for the above-described components in a professional digital camera 60 is depicted in FIG. 2. A camera body 62 including a lens, an aperture, a shutter (not shown), is coupled to a computer board 64 and an imager board 66. A captured image including the white balance reference is provided to a processing board 68 where white balance determination processing is performed. The resulting white balance is stored in a memory 70 of computer board 64 for processing pictures taken at the current venue and in one or more
10 non-volatile memory cards inserted into one of several card memory slots 72 for current or future picture taking sessions at this venue. A display board 74 controls the display and provides an interface to various control buttons.

Obtaining a white balance setting involves capturing an image of a white balance reference in the scene and it can sometimes be difficult to
15 accomplish this when the user arrives at a venue during the particular entertainment, such as arriving after a football game has started. With this problem in mind, white balance capture and image processing can be performed in a number of different scenarios. The user can go to a venue in advance and capture a white balance for the venue, store the white balance image, process the
20 image using the computer 38, store the white balance for the venue on the removable memory card 32 and use the white balance from the removable memory card 32 to process venue images in the digital camera at the venue when the user returns to the venue so that the images can be immediately sent for publication. Alternatively, the user can capture the venue images, associate the
25 images with the white balance setting and process the images using the computer 38. Another scenario involves capturing the white balance reference image at the venue event, processing the reference image in the digital camera at the event to obtain the white balance, storing the white balance in a file on the removable memory card 32 with an associated venue/file name, capturing venue event
30 images, and processing the event images in the digital camera using the white balance captured at the event. Another alternative is to use the white balance

captured/determined at the venue event to later process the images in the computer 38.

The white balance capture, storage and use operations of the present invention are depicted in FIG. 3 for the scenario where the user visits the venue ahead of time, and the digital camera includes sufficient processing power to determine a white balance and process the captured images with a stored white balance setting. Typically the user will go to a first venue (operation 102) and take a photograph of a neutral object in the scene (operation 104), such as the neutral white balance reference card discussed above, under the expected lighting conditions. At this time the user will typically store this image in memory of the removable memory card 32. The image is then processed (operation 106) by the digital camera to determine the white balance settings. Alternatively, the image can be processed to determine the white balance on the computer 38. The user then uses a digital camera graphical user interface (GUI) and associated digital camera buttons (not shown) to select a mode for storing the white balance setting (operation 108). This operation 108 can also be performed in computer 38. The user, via the GUI, enters (or selects/confirms) a file name for the white balance setting (operation 110) and the setting is stored in removable memory card 32 (operation 112) which, if located in the computer 38, would be removed and inserted into the digital camera. The naming would also occur in the computer 38 when the white balance processing is not performed by the digital camera. The user then goes to a second venue (operation 114) and repeats the operations noted above (operation 116). The user goes to the next/last venue (operation 118) and repeats the operations (operation 120).

When the user returns to the first venue (operation 122), the user selects the mode for white balance setting in the digital camera (operation 124) and selects the file name of the first venue (operation 126). The digital camera accesses the memory card 32, and obtains the white balance settings from the file using the file name (operation 128). The user takes new photographs at the venue event (operation 130) and the digital camera applies the white balance setting to correct each photograph (operation 132) where each corrected photograph is

stored in memory card 32. The images can then be output by removing the memory card 32 and downloading the images using the computer 38 or, if the digital camera has an output port, downloading over a connection to the port.

FIG. 4 depicts the flow of operations of white balance management within the digital camera. User actions for the white balance function occur through activation of a white balance button on the digital camera. This button is preferably a physical button but could be a GUI button projected onto the digital camera display and activated via a pointer moved by physical buttons.

The buttons discussed hereinafter are preferably GUI buttons that are pointed to and activated by the physical buttons depicted in FIG. 2. The buttons could, of course, be physical buttons initiating the appropriate functions.

When a determination is made that there are no images in a currently active camera file or folder stored on one of the detachable memory cards 32/72 and the white balance button is pressed (operation 152), a message screen 180 (see FIG. 5A) indicating that no image is selected is displayed on the display 21 (operation 154). Pressing the "OK" button 182 turns off the LCD. Pressing the "Option" button 184 presents a White Balance Setting screen 194 (see FIG. 5C) (operation 156).

When the currently active folder contains images and the white balance button is pressed, an image selection screen 186 (see FIG. 5B) portraying the currently active image and the query "Use image n?" is displayed, where n is the number assigned to that image by the digital camera control system. When the digital camera does not have the capability of entering an alphanumeric name through a keyboard or GUI, the number n is also the name of the folder or file containing the white balance setting. If the image LCD is off when the white balance button is pressed, it will be turned on and the above mentioned screen displayed. Pressing the "OK" button 188 loads the white balance values associated with that image. If the image LCD was on, the previously active function or menu is displayed. If the image LCD was off, this display is returned to the off state. Pressing the "Cancel" button 190 returns the user to the previously displayed function or menu; if the image LCD was off, this display is

turned off. Pressing the "Options" button 192 displays a White Balance Setting Menu 194 (see FIG. 5C). This menu displays a number of items, as described below.

When the "Option" button 192 on the "Use Image n?" menu screen (FIG. 5B) is pressed, a screen 194 (FIG. 5C) presenting a menu of White Balance options is presented (operation 157). The items displayed in this screen 194 include: a list 196 of white balance files that exist in the digital camera; an option 198 to load settings from a memory card; and an option 200 to delete white balance settings from the digital camera. The currently active white balance setting is noted by a "." symbol. Choosing any of the white balance settings via the control buttons of the digital camera activates that white balance value, and returns the image LCD to its previous state. The selected white balance setting persists until changed by the user. Choosing the "Load from CARD..." option 198 results in the digital camera producing (operation 158) a white balance sub-menu 202 (see FIG. 5D) that offers options for selecting white balance files that may exist on either or both of the removable memory cards in the digital camera. Selecting one of the displayed white balance options loads the white balance values from that file into memory, and returns the user to the updated White Balance Setting menu 194 (FIG. 5C), which displays the name of the just-loaded white balance file. If an attempt is made to load a white balance setting whose name matches an already-existing setting, a message screen 204 (see FIG. 5E) will be displayed (operation 160). This screen poses the question whether or not to replace the existing file. Pressing the "Yes" button 206 loads/replaces the white balance setting. Pressing the "No" button 208 does not load the file from the card and returns the user to the White Balance Setting menu (FIG. 5C).

If a memory card having no white balance files is accessed, a no file message screen 210 (FIG. 5F) will be displayed. Pressing the "OK" button 212 returns the user to the White Balance Setting menu 194. If the maximum number of white balance files allowed is reached and an attempt is made to load another file, a maximum number message screen 214 (FIG. 5G) is displayed. Pressing the "OK" button 216 returns the user to the White Balance Setting menu

194. In such a situation, to load additional white balance files into camera memory, the user must first delete one or more white balance files from the digital camera. If the maximum number of white balance files already exists when the "Load from card..." option in the White Balance Setting screen 194 is selected, the message screen 214 (FIG. 5G) is displayed.

Generally, each digital camera can utilize white balance files generated by that digital camera only. If an attempt is made to load white balance files from another digital camera, the invalid file message 218 (FIG. 5H) is displayed. Pressing the "OK" button 220 returns the user to the White Balance Setting menu 194.

Choosing the "Delete WB setting..." option in the White Balance menu 194 displays (operation 162) a white balance sub-menu screen 222 (FIG. 5I) with options for deleting white balance files that exist in the digital camera. Selecting one of the white balance settings from this sub-menu displays (operation 164) a confirmation screen 224 (FIG. 5J). Selecting the "Yes" option 226 deletes the selected setting from the digital camera and returns the user to the White Balance Setting menu 194. Selecting the "No" option 228 does not delete the selected setting and returns the user to the White Balance Setting menu 194. If the currently active white balance setting is deleted, the current setting is set to "Untitled."

If there are no white balance settings in the digital camera and the "Delete WB setting..." option 200 is selected, a no setting message 230 (FIG. 5K) is displayed (operation 166). Pressing the "OK" button 232 returns the user to the White Balance Setting screen 194 (see FIG. 5C).

The present invention has been described with respect to communicating with the digital camera via memory cards. It is possible to transfer the settings from one digital camera to another, or to and from a computer, using a wired or wireless communication link.

The present invention has been described with respect to determining settings from a white balance reference. The present invention can include the capturing of a calibration image of a color chart instead of just a gray

card. The digital camera or computer software would locate and analyze the patches in the color chart and create both a custom white balance and color correction matrix for the venue with the remainder of the process being the same.

- The many features and advantages of the invention are apparent
- 5 from the detailed specification and, thus, it is intended by the appended claims to cover all such features and advantages of the invention which fall within the true spirit and scope of the invention. Further, since numerous modifications and changes will readily occur to those skilled in the art, it is not desired to limit the invention to the exact construction and operation illustrated and described, and
- 10 accordingly all suitable modifications and equivalents may be resorted to, falling within the scope of the invention.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
22

Parts List

10	System
12/60	Digital Camera
14	Lens
16	Sensor
18	Diode
19	Viewfinder
20	Display memory
21	Display
22	Buttons
23	Exposure determination unit
24	Camera control unit
25	Aperture driver
26	Aperture
27	Analog processing unit
28	A/D converter
29	Frame memory
30	Color processing unit
31	Interface
32	Removable memory card
34	White balance determination unit
36	White balance memory
38	Computer
62	Body
64	Computer board
66	Imager board
68	Processing board
70	Memory
72	Memory slots
74	Display board
102 - 132	Setting and processing operations

152 - 166	White balance file management operations
180 - 232	Graphical user interface display elements